




Europäisches
Patentamt

EP 09 / 8361
European
Patent Office

PCT/EP 99 / 08361
4
Office européen
des brevets



Bescheinigung

Certificate

Attestation

Die angehefteten Unterlagen stimmen mit der ursprünglich eingereichten Fassung der auf dem nächsten Blatt bezeichneten europäischen Patentanmeldung überein.

The attached documents are exact copies of the European patent application described on the following page, as originally filed.

Les documents fixés à cette attestation sont conformes à la version initialement déposée de la demande de brevet européen spécifiée à la page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

98121134.5

**PRIORITY
DOCUMENT**
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts:
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN
THE HAGUE,
LA HAYE, LE

24/03/00



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation

Anmeldung Nr.:
Application no.: 98121134.5
Demande n°:

Anmeldetag:
Date of filing: 10/11/98
Date de dépôt:

Anmelder:
Applicant(s):
Demandeur(s):
SIEMENS AKTIENGESELLSCHAFT
80333 München
GERMANY

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:

Method and apparatus for determining properties of a signal transmission channel

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:
H04L25/49, H04L5/14, H04L12/26

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE
Etats contractants désignés lors du dépôt:

Bemerkungen:
Remarks:
Remarques:

This Page Blank (uspto)

GR 98 P 4747

EPC - Munich
12

10. Nov. 1998

1

Description

Method and apparatus of determining properties of a signal transmission channel

5

The invention relates to a method of determining properties of a signal transmission channel between a first subscriber end point and a second subscriber end point of a telephone network having a plurality of subscribers, wherein a first subscriber terminal is connected to said first subscriber end point and a second subscriber terminal is connected to said second subscriber end point, wherein said telephone network upon request of a subscriber establishes a signal transmission channel between said first subscriber and said second subscriber, wherein said first subscriber end point is connected to the telephone network by a digital channel portion. The invention further relates to a subscriber terminal in a telephone network having a plurality of subscribers, wherein said telephone network upon request of a subscriber establishes a signal transmission channel between selected subscribers, said subscriber terminal being connected to a subscriber end point of said telephone network.

25 Recently, substantial progress has been made in increasing the data transmission rates when transmitting data over conventional analogue telephone lines. The International Telecommunications Union (ITU) has promulgated and published various recommendations, such as V.32, V.32bis, or V.34, that
30 are concerned with data transmission over telephone lines. These recommendations are all based on a transmission technique called quadrature amplitude modulation (QAM). QAM has proven advantageous for the plain old telephone system (POTS) environment.

35

Nevertheless, the network of telephone system has undergone massive changes in that the network is nowadays almost

GR 98 P 4747

2

entirely digital. The analogue signals originating from a first subscriber modem are converted at the subscriber's central office to digital representations which are carried through the digital telephone network. At the central office of a second subscriber, the digital signals are converted back into analogue signals to be driven into a second subscriber's subscriber line. The second subscriber's modem interprets the analogue signals on the analogue subscriber line by demodulating the QAM signals produced by the first subscriber's modem. The same way of data communication is carried out in the reverse direction.

Increasingly more subscribers are connected to the telephone network through a digital subscriber interface, such as ISDN. Thus, many data connections are established between a first subscriber having an analogue network interface and a second subscriber having a digital network interface. In many cases, the second subscriber will be an internet service provider. In order to optimise data transmission over such heterogeneous communication channels, various proposals have been made in the recent past. One such proposal is known from US 5,801,695.

The proposal is based on the idea that the transmission rate in a heterogeneous communication channel from the digital subscriber to the analogue subscriber may be raised by using a PCM coding technique instead of the former QAM modulation techniques. The PCM coding technique uses a plurality of signal levels for encoding data symbols (each data symbol comprising multiple bits). These signal levels are again recognised by the receiving modem which is then able to decode the data symbol encoded into the signal levels.

Further, ITU has promulgated a new recommendation V.90 in September 1998. The new recommendation also relies on a PCM coding technique for the transmission of data from the digital subscriber to the analogue subscriber. Draft

recommendation V.90 in terms of its PCM coding scheme depends on ITU-T recommendation G.711 describing Pulse Code Modulation (PCM) of Voice Frequencies which is generally applied in telephone networks throughout the world when

5 converting analogue signal amplitude values into numeric representations thereof, and vice versa. G.711 recommends two PCM coding schemes generally known as μ -law, which is applied in North American telephone networks, and A-law, which is applied in most other telephone networks. Both coding schemes

10 have in common that they have a logarithmic coding characteristic, i.e. the lower the signal amplitude value to be encoded, the more fine-grain the available PCM codes. Such logarithmic coding characteristic has been found to be particularly advantageous for encoding analogue voice signals

15 at minimum distortion.

Recommendation G.711 makes available 256 PCM codes (or U-codes as called in V.90) which are grouped into eight positive and eight negative segments (or U-chords as called

20 in V.90). Each PCM code is encoded using eight bits. Due to power restrictions on the analogue telephone line and due to line impairments, the analogue modem (according to the terminology used in the draft to V.90) receiving analogue amplitude values is unable to discriminate between all 256

25 available PCM codes. Therefore, a reduced set of PCM codes is determined for encoding data symbols during set-up of a data communication channel under real world conditions. This accordingly lowers the data transmission rate down from the maximum theoretical possible value of 64 kbit/s such that it

30 is not above 56 kbit/s.

ITU-T Recommendation V.90 assumes an environment where one subscriber terminal of a connection is connected to the telephone network through a digital line and the other

35 subscriber terminal of the connection is connected to the telephone network through an analogue line. However, in many instances, both subscriber terminals of a connection are

GR 98 P 4747

4

connected to the telephone network through a digital connection. This situation would allow to establish an all-digital channel between the two subscriber terminals at a data rate of 64 kbit/s, which is the standard data rate in
5 telephone networks.

US 5,151,398 discloses modem line probing signal techniques. These probing techniques relate to former analogue line modems defined for example in ITU-T V.34.

10

It is an object of the invention to provide a line probing scheme in order to detect an all-digital connection path between subscriber terminals of a telephone network.

15 This object is achieved by a method having the features of claim 1 or claim 4. The object is further achieved by an apparatus having the features of claim 11 or claim 12. Advantageous embodiments thereof are set out in the respective dependent claims.

20

A first embodiment of the invention pertains to a method of determining properties of a signal transmission channel between a first subscriber end point and a second subscriber end point of a telephone network having a plurality of
25 subscribers. A first subscriber terminal is connected to said first subscriber end point and a second subscriber terminal is connected to said second subscriber end point. Said telephone network upon request of a subscriber establishes a signal transmission channel between said first subscriber and
30 said second subscriber. Said first subscriber end point is connected to the telephone network by a digital channel portion. In a first step, said first subscriber terminal sends to said second subscriber terminal a digital probing signal comprising a sequence of frames, each frame comprising
35 a sequence of digital symbols, each symbol having a plurality of bits. The digital values of all symbols over all frames are equal except for one bit position of each symbol, the

GR 98 P 4747

5

value of which changes with every other frame. Said second subscriber terminal then receives a signal which is the result of said digital probing signal having been transmitted through said signal transmission channel. Said second

5 subscriber terminal evaluates said received signal by comparing said received signal with said digital probing signal. Eventually, said second subscriber terminal transmitting a response signal to said first subscriber terminal, said response signal carrying information about the
10 comparison result.

A second embodiment of the invention also concerns a method of determining properties of a signal transmission channel between a first subscriber end point and a second subscriber
15 end point of a telephone network having a plurality of subscribers. This method alternatively provides that said first subscriber terminal sends to said second subscriber terminal a digital probing signal comprising a sequence of frames, each frame comprising a sequence of digital symbols,
20 each symbol having a plurality of bits, wherein the digital values of all symbols are equal except for at least one pulse symbol of each frame having a significantly different digital value compared to the remaining equal values.

25 The line probing schemes proposed by the invention allow both to find out whether an all-digital transmission channel is present between said first subscriber end point and said second subscriber end point and further to find out the transmission properties of the all-digital transmission
30 channel. Since the transmission channels of most telephone networks are primarily intended for voice signal transmission, some networks impose digital signal impairments upon the digital signals carried through the network's channels. Such digital impairments include digital padding
35 (digital signal attenuation), robbed bit signalling, ADPCM (Advanced Differential Pulse Code Modulation) coding and voice compression algorithms. The latter impairments allow to

GR 98 P 4747

6

reduce the bit rate of 64 kbit/s generally reserved for a full channel to a lower rate without much sacrifice to the quality of voice signal transmission, thus making available bandwidth for other purposes. The methods of the invention
5 are capable of discriminating whether an all-digital channel is present and whether or not the all-digital channel has digital impairments. The methods of the invention are even capable of discriminating what kind of digital impairment is present in an all-digital transmission channel. Knowing the
10 kind of digital impairment allows the conclusion as to whether a transmission scheme between said first subscriber terminal and said second subscriber terminal is possible according to V.90 or another lower rate scheme such as V.34.

15 In the first embodiment, it is preferred that said one bit position is the most significant bit position. This way, the absolute digital value difference from one frame to another is as large as possible. It is even further preferred that said one bit position is the position of the sign bit. This
20 way of line probing ensures that no direct current is produced in an analogue channel portion which may be present in the transmission channel to be probed.

In the second embodiment, it is preferred that one bit
25 position of said at least one pulse symbol changes value with every other frame. Thus, frames can be identified as such more easily by the second subscriber terminal. In an even more preferred embodiment, said one bit position is the position of the sign bit. This ensures that no direct current
30 is produced in an analogue channel portion which may be present in the transmission channel to be probed.

In the second embodiment, it is preferred that the number of equal symbols per frame is significantly higher than the
35 number of pulse symbols. This allows said second subscriber terminal to clearly identify a pulse symbol as such. Preferably, there is one pulse symbol per frame.

GR 98 P 4747

7

Alternatively, there may be two pulse symbols per frame. It is most preferred that the total number of symbols per frame is 80.

5 Further advantages, features and areas of using the invention are explained in the following description of a preferred embodiment of the invention which is to be read in conjunction with the attached drawings. In the drawings:

10 Fig. 1a shows the configuration of an all-digital signal transmission path in the presence of digital impairment;

Fig. 1b shows the configuration of a signal transmission
15 path having an analogue portion;

Fig. 2 is a signal diagram of a probing signal and a received signal according to a first embodiment of the invention;

20 Fig. 3 depicts a digital symbol sequence of a probing signal and various received signals according to a second embodiment of the invention.

25 Fig. 1a illustrates an all-digital signal transmission path between a first subscriber terminal 1 and a second subscriber terminal 8. The first subscriber terminal 1 (a digital modem) is connected through a digital line portion 2 to a local digital switch 3. The local switch 3 is connected to a
30 digital transmission network 4 which forwards digital signals between subscribers of the transmission network. On the other end of the all-digital signal path, the second subscriber terminal 8 is connected through a digital line portion 7 to a local digital switch 6. The local switch 6 is connected to
35 the transmission network 4 through a digital impairment device 5. Fig. 1a shows an exemplary position of the digital impairment device within the transmission pat. The digital

GR 98 P 4747

8

impairment device may as well be part of any of the digital switches 3 and 6 or may be part of the transmission network 4 or of the transmission path 7.

- 5 Digital impairments include digital padding (digital signal attenuation), robbed bit signalling (RBS), and ADPCM (Advanced Differential Pulse Code Modulation) coding or other voice compression algorithms which may be imposed upon the signals passing through the impairment device 5. Digital
- 10 impairment devices are present in many existing transmission networks and have to be accounted for when trying to establish a connection between subscriber terminals of the network at the highest bit rate possible.
- 15 Fig. 1b shows a similar configuration as Fig. 1a except that the second subscriber terminal 8' is connected to the transmission network through an analogue line portion 7'. The transmission path of Fig. 1a consequently includes a hybrid device 9' which is connected to the analogue line portion 7'
- 20 and performs a four-wire to two-wire conversion. Additionally, the hybrid device 9' performs, on the four-wire side, a digital-to-analogue and an analogue-to-digital signal conversion so as to be connected to a digital switch 6'. The remaining structure of Fig. 1b corresponds to the one shown
- 25 in Fig. 1a. Thus, the description of the remaining elements may be referred to by similar reference numerals.

Both Fig. 1a and Fig. 1b illustrate exemplary structures of transmission paths that may be encountered when trying to

30 establish a connection between two subscribers of a transmission network wherein at least of the two subscribers is connected to the network through a digital line portion such as ISDN. Depending on the structure encountered on the transmission path between the subscribers, they may agree

35 upon a certain transmission scheme allowing a bit rate as high as possible for the encountered structure. Known transmission schemes are ITU-T V.34 using quadrature

GR 98 P 4747

9

amplitude modulation on analogue transmission paths and ITU-T V.90 using pulse amplitude modulation on transmission paths having both analogue and digital line portions. Further, pulse amplitude modulation according to ITU-T V.90 can also
5 be used as a transmission scheme on all-digital transmission paths.

Fig. 2 is a diagram of a probing signal of the first embodiment of the invention. The probing signal is
10 transmitted by the first subscriber terminal 1 and of a signal received by the second subscriber terminal 8 in the presence of a digital impairment device 5 introducing ADPCM to the signal transmission path between the first subscriber and the second subscriber. Terminal 1 sends 80 digital
15 symbols of equal value in a first frame and then sends 80 digital symbols of the same absolute value, however, being negative in sign. The probing signal consists of a plurality of frame pairs as illustrated in Fig. 2 subsequently transmitted by the first terminal 1.

20 In the presence of ADPCM in the transmission path, the received signal does not precisely follow the large signal swings from one frame to another. The second terminal 8 may interpret this as an all-digital transmission path which is
25 not transparent due to ADPCM. Such a connection is not capable of carrying an ITU-T V.90 transmission scheme.

Fig. 3 shows a digital symbol sequence of a probing signal (sequence a) transmitted by the first subscriber terminal 1
30 (Modem 1) according to a second embodiment of the invention and various cases of received signals (sequences b through g). Fig. 3 shows a frame structure of 9 symbols per frame. It is preferred to use a much higher symbol count per frame, preferably 80 symbols per frame. Each digital symbol shown in
35 Fig 3 is a hexadecimal representation of an 8 bit digital value corresponding to the U-code representation as defined in ITU-T V.90. The first symbol of the first probing frame in

GR 98 P 4747

10

sequence (a) is 4Ch (the character h indicating hexadecimal representation in this text). The first symbol of the second probing frame in sequence (a) is CCh, which is equal to 4Ch except for one bit position. According to ITU-T G.711, this
5 bit position is the sign bit of a signal represented by the digital symbol. All remaining symbols are at value 00h. Thus, the first symbol forms a signal pulse.

Sequence (b) of Fig. 3 shows the signal received by
10 subscriber terminal 8 (Modem 2) in the case of an all-digital, fully transparent connection. Thus the frame sent by modem 1 is received by modem 2 with identical symbols, merely displaced in time. This case allows to establish a PCM transmission scheme between modem 1 and modem 2. Sequence (b)
15 through (g) show received signals in the presence of digital impairments. Sequence (c) assumes an impairment of digital padding, i.e. the digital signal is attenuated. Thus the pulse symbol in the original probing sequence (a) is lower in its absolute value.

20 Sequence (d) shows a received signal in the presence of digital impairment in the form of robbed bit signalling (RBS). RBS is applied to a least significant bit of every sixth symbol. Thus, the received signal differs from the
25 original probing sequence every sixth symbol. Sequence (e) shows a received signal in the presence of both digital padding and RBS. Thus, the effects of both impairments appear as a superimposed effect on the received signal.

30 Finally, sequence (f) shows a received signal under the influence of ADPCM or another voice compression algorithm. The ADPCM coder cannot follow the high pulse symbol 4Ch of the probing sequence interspersed in the zero symbols 00h. Thus, the pulse symbol of modem 1 is received with a much
35 wider pulse width and less high amplitude in modem 2. This is a clear indication of ADPCM.

GR 98 P 4747

11

The invention generally also relates to a modem connected via a digital interface to a switched public telephone network. The modem communicates with a second modem also connected via a digital interface to the same switched public telephone network. Thus, there may exist the possibility to set up a connection between both modems with a transmission rate of 64 kbit/s on the basis of coding voice signals with pulse code modulation according to ITU-T recommendation G.711. The public telephone network may incorporate voice compression devices (ADPCM G.726, G.723 etc.), digital pads (digital attenuators), robbed bit signalling and echo cancelling devices.

Under such circumstances, digital encoding schemes like pulse amplitude modulation according to ITU-T V. 90 instead of known analogue schemes like ITU-T V.34 may be utilised to transfer data. In order to apply such a digital coding scheme, it needs to be assured that an all-digital channel has been established between the modems. Assuring this may be carried out by an appropriate probing signal sent through the transmission channel. Known probing techniques have proven that they cannot discriminate all possible channel configurations.

The probing sequence of the invention uses large amplitude changes in a symbol sequence (each symbol having a duration of 125 μ s). The meaning of amplitude relates to the definition of ITU-T recommendation G.711. After that single amplitude change, the signal may return to the previous value or continue with the new amplitude value for a number of symbols. The number of symbols is selected to be larger than any expected impulse response of a digital impairment of the channel. The amplitude value change must be large enough to produce a sufficient result in the presence of digital pads with or without the presence of RBS.

GR 98 P 4747

12

The receiving modem will evaluate the received symbols and search for amplitude changes. If these changes occur only for one symbol per frame and the following symbols either return to the previous value or remain at the new value, the connection is detected as capable to carry a V.90 transmission scheme. If, however, the symbols after an amplitude change do not remain at the new value or do not return to the value before the change (in other words there is an impulse response over time), it is determined, that a connection according to ITU-T V.90 is not possible. Typical impairments having an impulse response are voice compression algorithms and ADPCM, which may be regarded a compression algorithm, too. Whereas ADPCM has a characteristic impulse response to an change in amplitude, it depends on the design of a voice compression algorithm how large amplitude swings are processed and coded into the output signal of the voice compression coder.

Robbed bit signalling changes the least significant bit (LSB) in some symbols but leaves the remaining seven bits unchanged. A single amplitude change will therefore only be affected in the LSB, the remaining seven bits, however, will not change. Digital pads use conversion functions which defines an output value to a PCM input value thus providing digital attenuation. This function will only change the absolut value of the amplitude but it will not affect the behaviour of the signal over time.

In an implementation, modem 1 will generate a pattern as described in conjunction with Fig. 3 and sends the pattern through the transmission channel to modem 2. Modem 2 will receive a pattern which differs from the transmit pattern due to network impairments. Modem 2 will evaluate the pattern in the following way: It will first logical AND the pattern with FEh in order to ignore changes in the LSB. Next it will compare this new value with the previous one. If they are identical, a counter is incremented. If they are different,

GR 98 P 4747

13

then the current count value is compared to the expected value and if they differ, an error counter is incremented. Then the counter is reset to zero and the new value is transferred to the old value register. When all symbols have
5 been evaluated, the value of the error counter is compared to a fixed threshold value. If the error counter value is below the threshold, then it is determined that the connection is not capable of carrying an ITU-T V.90 type transmission scheme.

10

The appended program codes show how line probing signals according to the invention may be produced. The programs are based on a pseudo code. The program of appendix A corresponds to the embodiment of Fig. 2, and the program of appendix B
15 corresponds to the embodiment of Fig. 3. By no means are these program a limitation of the invention.

GR 98 P 4747

14

Appendix A

Example of program code for alternating pattern:

5

Transmit_Pattern:

Loop_COUNT = 20

10 High_Code = 4CH

Low_Code = CCH

Total_count = 100

For (i;I=0;I=Total_count)

15

{

For (j;J=1; j=Loop_Count)

SendPCMvalue (Low_code);

For (j;J=1;j=Loop_Count)

20

SendPCMvalue(High_Code);

}

Receiver:

Loop_Count = 20

25 Total_count = 100 * 2 * Loop_Count

Old = 0;

Error = 0;

Count = 0;

30

For (i;i=0;i=Total_count)

{

a = (GetnewPCMvalue() && 11111110B)

;Masked LSB

for RBS impact

35

If (Old <> a)

count++

ELSE

GR 98 P 4747

```

                                15
                                IF (COUNT <> LOOP_COUNT-1)
                                    Error++
                                count = 0
                                Old = a;
5      }

    If (Error > 1)
        Return (False)
    Return (True)
```

GR 98 P 4747

16

Appendix B

Example code for single value pattern detection:

5

Transmit_Pattern:

Loop_COUNT = 20

High_Code = 4CH

10 Low_Code = 00H

Total_count = 100

For (i;I=0;I=Total_count)

15

{

For (j;J=1; j=Loop_Count-1)

SendPCMvalue (Low_code);

SendPCMvalue(High_Code);

20

For (j;J=1; j=Loop_Count-1)

SendPCMvalue (Low_code);

SendPCMvalue(High_Code EXOR 80H);

25

}

Receiver:

Loop_Count = 20

30 Total_count = 100 * (LoopCount)

Old = 0;

Error = 0;

Count = 0;

35

For (i;i=0;i=Total_count)

{

GR 98 P 4747

```

                                17
      a = (GetnewPCMvalue() && 11111110B)      ;Masked LSB
for RBS impact
  If (Old <> a)
    count++
5    ELSE
    {
      IF (COUNT <> LOOP_COUNT-2)
        IF (COUNT <> 0)
          Error++
10      count = 0
      Old = a;
    }

  If (Error > 1)
15    Return (False)
  Return (True)
```



GR 98 P 4747

EPC - Munich
42

10. Nov. 1998

18

Claims

1. A method of determining properties of a signal transmission channel between a first subscriber end point and a second subscriber end point of a telephone network having a plurality of subscribers, wherein a first subscriber terminal (1) is connected to said first subscriber end point and a second subscriber terminal (8) is connected to said second subscriber end point, wherein said telephone network (3, 4, 5, 6) upon request of a subscriber establishes a signal transmission channel between said first subscriber and said second subscriber, wherein said first subscriber end point is connected to the telephone network by a digital channel portion (2), said method comprising the steps of:

said first subscriber terminal sending to said second subscriber terminal a digital probing signal comprising a sequence of frames, each frame comprising at least one frame portion, each frame portion comprising a sequence of digital symbols, each symbol having a plurality of bits, wherein each frame comprises a preset number of symbols, wherein the digital values of symbols in a frame portion are equal, and wherein the digital values of adjacent frame portions is significantly different;

said second subscriber terminal receiving a signal which is the result of said digital probing signal having been transmitted through said signal transmission channel;

said second subscriber terminal evaluating said received signal by comparing said received signal with said digital probing signal; and

said second subscriber terminal transmitting a response signal to said first subscriber terminal, said response signal carrying information about the comparison result.

GR 98 F 4747

19

2. The method of claim 1, characterised in that a frame comprises one frame portion (Fig. 2), wherein the digital values of all symbols over all frames are equal except for one bit position of each symbol, the value of which changes
5 with every other frame.

3. The method of claim 2, characterised in that said one bit position is the most significant bit position.

10 4. The method of claims 2 or 3, characterised in that said one bit position is the position of the sign bit.

5. The method of claim 1, characterised in that a frame comprises at least two frame portions (Fig. 3), wherein the
15 digital values of all symbols in a frame are equal except for at least one pulse symbol of each frame having a significantly different digital value compared to the remaining equal values.

20 6. The method of claim 5, characterised in that one bit position of said at least one pulse symbol changes value with every other frame.

7. The method of claim 6, characterised in that said one
25 bit position is the position of the sign bit.

8. The method of any of claims 5 to 7, characterised in that the number of equal symbols per frame is significantly higher than the number of pulse symbols.
30

9. The method any of claim 5 to 7, characterised in that there is one pulse symbol per frame.

10. The method of claim 5 or 6, characterised in that there
35 are two pulse symbols per frame.

GR 98 P 4747

20

11. The method of any of claims 5 to 10, characterised in that the total number of symbols per frame is 80.

12. In a telephone network having a plurality of subscribers, wherein said telephone network upon request of a subscriber establishes a signal transmission channel between selected subscribers, a subscriber terminal connected to a subscriber end point of said telephone network comprising:

10 means for connecting said subscriber terminal to said subscriber end point, said subscriber end point being connected to the telephone network by a digital channel portion,

15 means for sending to a second subscriber terminal, to which a signal transmission channel has been established, a digital probing signal comprising a sequence of frames, each frame comprising a sequence of digital symbols, each symbol having a plurality of bits, wherein the digital values of all symbols over all frames are equal except for one bit position of each symbol, the value of which changes with every other frame.

13. In a telephone network having a plurality of subscribers, wherein said telephone network upon request of a subscriber establishes a signal transmission channel between selected subscribers, a subscriber terminal connected to a subscriber end point of said telephone network comprising:

30 means for connecting said subscriber terminal to said subscriber end point, said subscriber end point being connected to the telephone network by a digital channel portion,

35 means for sending to said second subscriber terminal a digital probing signal comprising a sequence of frames, each frame comprising a sequence of digital symbols, each symbol

GR 98 P 4747

21

having a plurality of bits, wherein the digital values of all symbols are equal except for at least one symbol of each frame having a significantly different digital value compared to the remaining equal values.

EPO - Munich
42

10. Nov. 1998




Fig. 1a




Fig. 1b




Fig. 2

This Page Blank (uspro)

Abstract

The invention generally relates to a modem connected via a digital interface to a switched public telephone network and to method for probing the line properties. The modem communicates with a second modem also connected via a digital interface to the same switched public telephone network. The public telephone network may incorporate voice compression devices (ADPCM G.726, G.723 etc.), digital pads (digital attenuators), robbed bit signalling and echo cancelling devices. The probing sequence of the invention uses large amplitude changes in a symbol sequence (each symbol having a duration of 125 μ s). After that single amplitude change, the signal may return to the previous value or continue with the new amplitude value for a number of symbols. The number of symbols is selected to be larger than any expected impulse response of a digital impairment of the channel. The amplitude value change must be large enough to produce a sufficient result in the presence of digital pads with or without the presence of RBS.

This Page blank (uspto)